



FC C

Mocowanie kabla do kształtownika 40x22 mm

Materiał: Stal nierdzewna AISI 304
 Poliamid z włóknem szklanym koloru czarnego, odporny na działanie promieni UV.

Rodzaj	Kod	Typ kabla	D	L	h ₁	h _{max}				
	FCC 1 x 5 mm	CNT 200	4,9 – 5,1	22	23	53	4	50	3,6	
	FCC 1 x 6,1mm	CNT 240	5,9 – 6,2	22	23	53	4	50	3,6	
	FCC 1 x (...)	Fiber optic	all diameter	22	23	53	4	50	3,6	
	FCC 1 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	23	53	4	50	3,6	
	FCC 1 x 1/4" (9)	LDF 1-50	8 – 9,2	22	23	53	4	50	3,5	
	FCC 1 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	23	53	4	50	3,5	
	FCC 1 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	23	53	4	50	3,5	
	FCC 1 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	28	58	4	50	3,5	
	FCC 1 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	28	58	4	50	3,5	
	FCC 1 x (...)	Power cable		34	28	58	4	50	3,2	
	FCC 1 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	44	74	6	50	6,2	
	FCC 1 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	44	74	6	50	5,7	
	FCC 1 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	67	107	8	50	9,0	
	FCC 1 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	68	108	8	50	11,0	
	FCC 1 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	80	120	8	25	7,5	
	FCC 2 x 5 mm	CNT 200	4,9 – 5,1	22	43	73	4	50	5	
	FCC 2 x 6,1mm	CNT 240	5,9 – 6,2	22	43	73	4	50	5	
	FCC 2 x (...)	Fiber optic	all diameter	22	43	73	4	50	5	
	FCC 2 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	43	73	4	50	5	
	FCC 2 x 1/4" (9)	LDF 1-50	8 – 9,2	22	43	73	4	50	5	
	FCC 2 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	43	73	4	50	5	
	FCC 2 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	43	73	4	50	5	
	FCC 2 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	48	78	4	50	4,9	
	FCC 2 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	48	78	4	50	4,9	
	FCC 2 x (...)	Power cable		34	48	78	4	50	4,7	
	FCC 2 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	83	113	6	50	9	
	FCC 2 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	83	113	6	50	10	
	FCC 2 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	118	158	8	25	7,2	
	FCC 2 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	130	170	8	25	9	
	FCC 2 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	153	193	8	20	9,2	
FCC 3 x 5 mm	CNT 200	4,9 – 5,1	22	63	93	4	50	6,5		
FCC 3 x 6,1mm	CNT 240	5,9 – 6,2	22	63	93	4	50	6,5		
	FCC 3 x (...)	Fiber optic	all diameter	22	63	93	4	50	6,5	
	FCC 3 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	63	93	4	50	6,5	
	FCC 3 x 1/4" (9)	LDF 1-50	8 – 9,2	22	63	93	4	50	6,5	
	FCC 3 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	63	93	4	50	6,5	
	FCC 3 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	63	93	4	50	6,5	
	FCC 3 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	68	98	4	50	6	
	FCC 3 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	68	98	4	50	6	
	FCC 3 x (...)	Power cable		34	68	98	4	50	6	
	FCC 3 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	122	152	6	50	13	
	FCC 3 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	122	152	6	50	13,3	
	FCC 3 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	168	208	8	25	9,2	
	FCC 3 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	193	233	8	25	11,7	
	FCC 3 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	227	237	8	20	12	
		FCC 4 x 5 mm	CNT 200	4,9 – 5,1	22	82	112	4	50	8
		FCC 4 x 6,1mm	CNT 240	5,9 – 6,2	22	82	112	4	50	8
FCC 4 x (...)		Fiber optic	all diameter	2	82	112	4	50	8	
FCC 4 x 8 mm		RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	82	112	4	50	7,7	
FCC 4 x 1/4" (9)		LDF 1-50	8 – 9,2	22	82	112	4	50	7,7	
FCC 4 x 1/4" (10)		LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	82	112	4	50	7,7	
FCC 4 x 1/4" (11)		RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	82	112	4	50	7,7	
FCC 4 x 3/8" (14)		RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	88	118	4	50	8	
FCC 4 x 1/2" (17)		RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	88	118	4	50	8	
FCC 4 x (...)		Power cable		34	88	118	4	50	8	
FCC 4 x 19,5		MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	161	191	6	50	9,7	
FCC 4 x 7/8" (28)		RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	161	191	6	50	9,6	
FCC 4 x 1.1/4" (40)		RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	218	258	8	25	11	
FCC 4 x 1.5/8" (52)		RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	256	296	8	25	12,5	
FCC 4 x 2.1/4" (60)		RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	227	329	8	15	8	
	FCC 4 x (...) 2R	Fiber optic		34	44	74	4	50	7	
	FCC 4 x 1/4" (10)	2R LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	34	44	74	4	50	7	
	FCC 4 x 1/4" (11)	2R RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	34	44	74	4	50	7	