



FC A5

Mocowanie kabla do kątownika 50 mm

Materiał: Stal nierdzewna AISI 304
 Poliamid z włóknem szklanym koloru czarnego, odporny na działanie promieni UV.

Rodzaj	Kod	Typ kabla	D	L	h _{max}	h ₁			
	FCA4 1 x 5 mm	CNT 200	4,9 – 5,1	22	23	68	4	50	3,6
	FCA4 1 x 6,1mm	CNT 240	5,9 – 6,2	22	23	68	4	50	3,6
	FCA4 1 x (...)	Fiber optic	all diameter	22	23	68	4	50	3,6
	FCA4 1 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	23	68	4	50	3,6
	FCA4 1 x 1/4" (9)	LDF 1-50	8 – 9,2	22	23	68	4	50	3,5
	FCA4 1 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	23	68	4	50	3,5
	FCA4 1 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	23	68	4	50	3,5
	FCA4 1 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	28	73	4	50	3,5
	FCA4 1 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	28	73	4	50	3,2
	FCA4 1 x (...)	Power cable		34	44	89	6	50	6,2
	FCA4 1 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	44	89	6	50	6,2
	FCA4 1 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	44	89	6	50	5,7
	FCA4 1 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	67	117	8	50	9,0
	FCA4 1 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	68	113	8	50	11,0
	FCA4 1 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	80	130	8	25	7,5
	FCA4 2 x 5 mm	CNT 200	4,9 – 5,1	22	43	88	4	50	5
	FCA4 2 x 6,1mm	CNT 240	5,9 – 6,2	22	43	88	4	50	5
	FCA4 2 x (...)	Fiber optic	all diameter	22	43	88	4	50	5
	FCA4 2 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	43	88	4	50	5
	FCA4 2 x 1/4" (9)	LDF 1-50	8 – 9,2	22	43	88	4	50	5
	FCA4 2 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	43	88	4	50	5
	FCA4 2 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	43	88	4	50	5
	FCA4 2 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	48	93	4	50	4,9
	FCA4 2 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	48	93	4	50	4,7
	FCA4 2 x (...)	Power cable		34	83	128	6	50	10
	FCA4 2 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	83	128	6	50	10
	FCA4 2 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	83	128	6	50	10
	FCA4 2 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	118	168	8	25	7,2
	FCA4 2 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	130	180	8	25	9
	FCA4 2 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	153	203	8	20	9,2
	FCA4 3 x 5 mm	CNT 200	4,9 – 5,1	22	63	108	4	50	6,5
	FCA4 3 x 6,1mm	CNT 240	5,9 – 6,2	22	63	108	4	50	6,5
	FCA4 3 x (...)	Fiber optic	all diameter	22	63	108	4	50	6,5
	FCA4 3 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	63	108	4	50	6,5
	FCA4 3 x 1/4" (9)	LDF 1-50	8 – 9,2	22	63	108	4	50	6,5
	FCA4 3 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	63	108	4	50	6,5
	FCA4 3 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	63	108	4	50	6,5
	FCA4 3 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	68	113	4	50	6
	FCA4 3 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	68	113	4	50	6
	FCA4 3 x (...)	Power cable		34	122	167	6	50	13,3
	FCA4 3 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	122	167	6	50	13,3
	FCA4 3 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	122	167	6	50	13,3
	FCA4 3 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	168	218	8	25	9,2
	FCA4 3 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	193	243	8	25	11,7
	FCA4 3 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	227	277	8	20	12
	FCA4 4 x 5 mm	CNT 200	4,9 – 5,1	22	82	127	4	50	8
	FCA4 4 x 6,1mm	CNT 240	5,9 – 6,2	22	82	127	4	50	8
	FCA4 4 x (...)	Fiber optic	all diameter	22	82	127	4	50	8
	FCA4 4 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	82	127	4	50	7,7
	FCA4 4 x 1/4" (9)	LDF 1-50	8 – 9,2	22	82	127	4	50	7,7
	FCA4 4 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	82	127	4	50	7,7
	FCA4 4 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	82	127	4	50	7,7
	FCA4 4 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	88	133	4	50	8
	FCA4 4 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	88	133	4	50	8
	FCA4 4 x (...)	Power cable		34	161	206	6	25	9,6
	FCA4 4 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	161	206	6	25	9,6
	FCA4 4 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	161	206	6	25	9,6
	FCA4 4 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	218	268	8	25	11
	FCA4 4 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	256	306	8	25	12,5
	FCA4 4 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	227	349	8	15	8
	FCA4 4 x (...) 2R	Fiber optic		34	44	89	4	50	7
	FCA4 4 x 1/4" (10) 2R	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	34	44	89	4	50	7
	FCA4 4 x 1/4" (11) 2R	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	34	44	89	4	50	7