



FC B20

Mocowanie kabla na płaskownik,
rurę 3-20 mm

Materiał: Stal nierdzewna AISI 304
Poliamid z włóknem szklanym koloru czarnego,
odporny na działanie promieni UV.

Rodzaj	Kod	Typ kabla	D	L	h ₁	h _{max}			
	FCB 1 x 5 mm	CNT 200	4,9 – 5,1	22	23	53	4	50	3,6
	FCB 1 x 6,1mm	CNT 240	5,9 – 6,2	22	23	53	4	50	3,6
	FCB 1 x (...)	Fiber optic	all diameter	22	23	53	4	50	3,6
	FCB 1 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	23	53	4	50	3,6
	FCB 1 x 1/4" (9)	LDF 1-50	8 – 9,2	22	23	53	4	50	3,5
	FCB 1 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	23	53	4	50	3,5
	FCB 1 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	23	53	4	50	3,5
	FCB 1 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	28	58	4	50	3,5
	FCB 1 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	28	58	4	50	3,5
	FCB 1 x (...)	Power cable		34	28	58	4	50	3,2
	FCB 1 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	44	74	6	50	6,2
	FCB 1 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	44	74	6	50	5,7
	FCB 1 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	67	107	8	50	9,0
	FCB 1 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	68	108	8	50	11,0
FCB 1 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	80	120	8	25	7,5	
	FCB 2 x 5 mm	CNT 200	4,9 – 5,1	22	43	73	4	50	5
	FCB 2 x 6,1mm	CNT 240	5,9 – 6,2	22	43	73	4	50	5
	FCB 2 x (...)	Fiber optic	all diameter	22	43	73	4	50	5
	FCB 2 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	43	73	4	50	5
	FCB 2 x 1/4" (9)	LDF 1-50	8 – 9,2	22	43	73	4	50	5
	FCB 2 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	43	73	4	50	5
	FCB 2 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	43	73	4	50	5
	FCB 2 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	48	78	4	50	4,9
	FCB 2 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	48	78	4	50	4,9
	FCB 2 x (...)	Power cable		34	48	78	4	50	4,7
	FCB 2 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	83	113	6	50	9
	FCB 2 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	83	113	6	50	10
	FCB 2 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	118	158	8	25	7,2
	FCB 2 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	130	170	8	25	9
FCB 2 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	153	193	8	20	9,2	
	FCB 3 x 5 mm	CNT 200	4,9 – 5,1	22	63	93	4	50	6,5
	FCB 3 x 6,1mm	CNT 240	5,9 – 6,2	22	63	93	4	50	6,5
	FCB 3 x (...)	Fiber optic	all diameter	22	63	93	4	50	6,5
	FCB 3 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	63	93	4	50	6,5
	FCB 3 x 1/4" (9)	LDF 1-50	8 – 9,2	22	63	93	4	50	6,5
	FCB 3 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	63	93	4	50	6,5
	FCB 3 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	63	93	4	50	6,5
	FCB 3 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	68	98	4	50	6
	FCB 3 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	68	98	4	50	6
	FCB 3 x (...)	Power cable		34	68	98	4	50	6
	FCB 3 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	122	152	6	50	13
	FCB 3 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	122	152	6	50	13,3
	FCB 3 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	168	208	8	25	9,2
	FCB 3 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	193	233	8	25	11,7
FCB 3 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	227	237	8	20	12	
	FCB 4 x 5 mm	CNT 200	4,9 – 5,1	22	82	112	4	50	8
	FCB 4 x 6,1mm	CNT 240	5,9 – 6,2	22	82	112	4	50	8
	FCB 4 x (...)	Fiber optic	all diameter	22	82	112	4	50	8
	FCB 4 x 8 mm	RFF 1/4" -50, SCF 14-50, FSJ1-50A	7 – 8	22	82	112	4	50	7,7
	FCB 4 x 1/4" (9)	LDF 1-50	8 – 9,2	22	82	112	4	50	7,7
	FCB 4 x 1/4" (10)	LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	22	82	112	4	50	7,7
	FCB 4 x 1/4" (11)	RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	22	82	112	4	50	7,7
	FCB 4 x 3/8" (14)	RFF 1/2"-50, SCF 12-50, FSJ4-50B	13 - 14	22	88	118	4	50	8
	FCB 4 x 1/2" (17)	RF 1/2"-50, LCF 12-50, LDF4-50A	16 - 17	22	88	118	4	50	8
	FCB 4 x (...)	Power cable		34	88	118	4	50	8
	FCB 4 x 19,5	MCMK 2 x 16 + 16 Feederless DC cable	19,3-19,8	34	161	191	6	50	9,7
	FCB 4 x 7/8" (28)	RF 7/8"-50, LCF78-50A, LDF5-50A	27 – 28	34	161	191	6	50	9,6
	FCB 4 x 1.1/4" (40)	RF1 1/4"-50, LCFS 114-50A, LDF6-50	39 – 40	46	218	258	8	25	11
	FCB 4 x 1.5/8" (52)	RF1 5/8"-50,LCF158-50A, LDF7-50A	50 – 52	58	256	296	8	25	12,5
FCB 4 x 2.1/4" (60)	RF 2 1/4"-50, LCF214-50A, LDF12-50	59 - 60	67	227	329	8	15	8	
	FCB 4 x ... 2R	Fiber optic	all diameter	34	44	74	4	50	7
	FCB 4 x 1/4" (10)	2R LCF 14-50, FSJ2-50, RG 8, RG 213, H 1000	9,8 – 10,5	34	44	74	4	50	7
	FCB 4 x 1/4" (11)	2R RF 3/8"-50, LCF38-50, LDF2-50, RG 214	10,5 – 11,5	34	44	74	4	50	7